

AM-50 Active Monitor



:: Product Description

- * Active studio monitor set equipped with 2x35Wrms amplifier
- * Stylish black design: fits in any modern interior
- * Solid wooden enclosure with black satin finish
- * Perfect for recording studio, home DJ booth, PC-speaker, I-Pod®, ...
- * Shielded magnet design (can be used next to a TV/PC Monitor)
- * Crystal clear sound with powerful bass response!
- * Flat frequency response from 65 to 20.000Hz
- * Uses ¾' dome tweeter + 5' Kevlar woofer
- * Can be connected to any line-level audio output

:: Technical Information

Power Supply: AC230V, 50Hz Fuse: 20mm glass fuse 250V 800mA slow Frequency response: 65-20.000Hz (+/-5dB) Line input: 750mV @ 10k Ohm Impedance passive cabinet: 4 Ohm Crossover freq: 2500Hz @ 12dB/oct Woofer: D= 5' (13cm) Kevlar cone Tweeter: D= ¾' (2cm) soft dome type Dimensions: 180(W) x 258(H) x 209(D) mm Weight: 6,3kg